



## U paketu:

- 1. uHoo senzor za kvalitet vazduha, USB adapter i USB kabl
- 2. Wi-Fi (802,11 b / g / n @ 2,4 GHz) WPA / WPA2. Mreža od 5 GHz nije podržana.
- 3. Mobilni telefon sa iOS 10 ili novijom verzijom
- 4. Instalirajte najnoviju aplikaciju "uHoo" sa https://apps.apple.com/us/app/uhoo/id1084953997.
- 5. Isključite VPN vezu na telefonu (ukoliko koristite VPN)
- 6. Povežite telefon na isti WI-Fi (na primer, "Moja mreža") na koji želite da se poveže vaš uHoo

## Dodavanje novog uHoo-a na iOS-u

1. Prijavite se sa svojim uHoo nalogom. Ako nemate uHoo nalog, idite na "Prijavi se" u gornjem desnom uglu i registrujte se za nalog. Nakon toga dobitićete e-poštu, kliknite na vezu da biste verifikovali i aktivirali svoj nalog.



2. Dodirnite "+" za dodavanje svog prvog uHoo-a.



	1:19 PM	@ 🕇 95% 🗰	
< Search			
	uHoo		
	uHoo Limited		
	<b></b>	٢	
3.0 ***	ដដ	4+	
14 Ratings		Age	
What's Ne	ew	Version History	
Version 7.0		1mo ago	
*New* Integr available	ation with Conrad Cor	nect is now	
*New* Integr available     Improved ap	ation with Conrad Cor	nect is now	
*New* Integr available     Improved ap  Preview	ation with Conrad Cor	nance	
*New* Integr available     Improved ap  Preview	eation with Conrad Cor p stability and perform	nect is now nance Ξ <sup>500</sup>	
*New* Integr available     • Improved ap  Preview  Correc*      E      here c020 r0      Scmmary      Be	ation with Conrad Cor up stability and perform 	Center Tips Bedroom: Nitrogen dice	
*New* Integr available     Improved ap  Preview  Correr      Deprovement      Deprovem	ation with Conrad Cor p stability and perform 	Carrier Tips Bedroom: Htrogen dice Opening windows of turn opening windows of turn	
*New* Integr available     Improved ap  Preview  Core *  Sommary Be      & Temperature     O Humidity	etion with Conrad Cor p stability and perform ()	Centre & sou Centre & sou Tips Badroom Hitrogen dist Cherring window of thrust Methodow Hitrogen dist Control previous Constant Interest devices constant Consta	
New* Integr available     Improved ap  Preview  Core     Summary     Be     temperature     O HumsBty     O Ar Pressure	ation with Conrad Cor p stability and perform and the stability and perform to the stability	Conv	
**New* Integr available     • Improved ap  Preview  Conve *  Source *	see ()	Cener  to not  the second seco	
New* Integr available     Improved ap  Preview  Genve  Genve Genve  Genve  Genve  Genve  Genve  Genve	ation with Conrad Cor p stability and perform to a set to a	Annue and a second seco	





3. Povežite svoj uHoo sa bilo kojom utičnicom pomoću priloženog USB adaptera i kabla, potvrdite da je LED lampica na dnu uređaja PLAVA, u suprotnom sledite uputstva na ekranu da biste resetovali svoj uHoo. Uključite dozvolu za lokaciju da biste aplikaciji omogućili da identifikuje ime vaše Wi-Fi mreže.



4. Potvrdite da li je prikazana Wi-Fi mreža ("TP-Link\_951A" u ovom primeru) takođe ona na koju želite da se poveže vaš uHoo uređaj. Ako želite da ga povežete sa drugom Wi-Fi mrežom, dodirnite "Idi na podešavanja", povežite telefon sa željenom Wi-Fi mrežom, a zatim se vratite u aplikaciju uHoo.







No SIM 🗢	1:21 PM	@ <b>1</b> 94% 🗰	<ul> <li>■ UMOD *</li> </ul>	T21PM @ 7 94%
$\leftarrow$			< Settings	Wi-Fi
			Wi-Fi	
			✓ TP-Link_951A	) چ 🕯
•			MY NETWORKS	
WI-F	uHoo_i	<i></i>	uHoo_A81B6A94	AEE04 🗢 🕄
			PLDTHOMEFIBR	88980 🔹 🕫 🚺
Connect	your phone to uH	loo Wi-Fi	PLDTHOMEFIBR	19bc28 🔒 😤 🚺
Go to Setting matches the of your uHoo VPN	is > Wi-Fi and select 1 MAC Address printed , then return to the ap s turned off on your p	the Wi-Fi that at the bottom op. Make sure phone.	Other	
You may saf	ely ignore the 'Unsecu message.	red Network'	Ask to Join Networ	ks Notify >
Can't fi Unplu	nd uHoo_###### in W ig uHoo and connect it	1-Fi list? again.	Known networks will be networks are available, y networks.	joined automatically. If no known you will be notified of available
			Auto-Join Hotspot	Ask to Join >



7.



6. Vratite se u aplikaciju uHoo kada vidite reč "Povezano" ispod Wi-Fi mreže "uHoo \_ ########## " I pojavi se simbol 奈na vrhu telefona. Možete zanemariti upozorenje "Bez interneta". Sačekajte dok telefon ne završi sa povezivanjem sa uređajem, ovo može potrajati do 45 sekundi.



8. Unesite svoju Wi-Fi lozinku (ako postoji) i dodirnite "Poveži". LED lampica uHoo-a postaće ZELENA što znači da je sada povezan na vašu Wi-Fi mrežu. NE ZATVARAJTE APLIKACIJU SADA.

SIM 🗢	1:22 PM	@ 🕫 94% 🔳
YOUR DEVICE		
uHoo_A81B6	SA9AEE04	
WI-FI NAME		
TP-Link_951	A	
WI-FI PASSWOI	RD	
		HIDE
Do not switch to	o a different Wi-Fi now.	
	Connect	

- 9. Ako posle 9. koraka lampica ostane PLAVA, sledite uputstva na ekranu telefona da biste resetovali uređaj i vratićete se na 5. korak da biste ponovo podesili svoj uHoo.





11. Nakon 9. koraka, vaš uHoo uređaj će se registrovati na uHoo "oblak". U zavisnosti od konfiguracije vaše Wi-Fi mreže, od vas će biti zatraženo da izaberete region za svoj uHoo.



12. Popunite osnovne informacije o svom uHoo-u i dodirnite "Nastavi" da biste dovršili postupak registracije, LED svetlo uHoo-a će se sada ISKLJUČITI. Takođe smo pružili nekoliko animiranih uputstava da objasnimo šta možemo očekivati od uređaja u narednih 48 sati.







13. Aplikacija uHoo će se vratiti na početnu stranicu sa prikazanim uređajem. Sačekajte najmanje 2 minuta pre nego što se aplikacija osveži kako bi prikazala vaše trenutne podatke o kvalitetu vazduha u vašem prostoru. Vaš uređaj za to vreme proverava da li postoji dostupno ažuriranje softvera. Ova stranica se osvežava svakog minuta, tako da nema potrebe da je ručno osvežavate. Takođe možete birati između dva različita dizajna prema vašim željama. Uživajte u svom odličnom vazduhu!

lo SIM	ŝ	1:28 PM	@ 🕈 90% 🖿
Ξ			(i)
Toda Bab	ny, 01:27 PM Ny's Room		
8	Temperature	-	31.7 ·c
٥	Humidity	-	73.2%
0	Air Pressure		990.5 hPa
0	CO2 still calibrating		1020 ppm
Ø	TVOC still calibrating	-	0 ppb
	PM2.5	-	6.0 <sup>µg/</sup> m3
q	со		0.0 ppm
8	NO2 still calibrating	-	19.4 ppb
0	Some ser	nsors are still calibra	ting >
	X		$\bigcirc$

## Napomene:

- 1. Ako želite da premestite uHoo u drugu sobu u vašem domu koja koristi istu WiFi mrežu, jednostavno isključite uHoo i uključite ga u drugoj sobi. uHoo će se automatski povezati na vašu mrežu. Ako je potrebno duže vreme za automatsko povezivanje, proverite da li je vaša Wi-Fi mreža dostupna u toj prostoriji.
- 2. Molimo ostavite da vaš uređaj radi 48 sati neprekidno nakon prvog podešavanja. Tokom prvog očitavanja rezultati će varirati kako biste saznali više o svom okruženju i kako bi se uređaj kalibrirao. Vaša stvarna očitavanja biće dostupna tek nakon 48 sati. Pre toga, očitavanja se zasnivaju na onome što uređaj saznaje o vašem okruženju.
- 3. Za više informacija o tome šta znači boja LED diode na uređaju, pogledajte dokument "Stanje vašeg uHoo" na <u>https://uhooair.com/setupguide</u>